

LSA 三相改单相 50Hz 220V/240V 功率。

					kVA: 220V 50Hz FF			
励磁系统					持续		备用	备用
型号	SHUNT	AREP	PMG	出线	H:125K	F:105K	H:150K	H:163K
LSA 40VS1	J6/4	C6/4	NA	12	7	6.5	7.5	8
LSA 40VS2	J6/4	C6/4	NA	12	9	8	9.5	10
LSA 40S3	J6/4	C6/4	NA	12	10.5	10	11.5	12
LSA 40S4	J6/4	C6/4	NA	12	12.5	11.5	13.5	14
LSA 40M5	J6/4	C6/4	NA	12	14	13	15	15.5
LSA 40M7	J6/4	C6/4	NA	12	15	14	16	16.5
LSA 42.3VS2	J6/4	C6/4	option	12	16	14.5	17	17.5
LSA 42.3VS3	J6/4	C6/4	option	12	19	17.5	20	21.0
LSA 42.3S4	J6/4	C6/4	option	12	22	20	23.5	24
LSA 42.3S5	J6/4	C6/4	option	12	25	23	26.5	27.5
LSA 42.3M7	J6/4	C6/4	option	12	27	24.5	28.5	29.5
LSA 42.3M8	J6/4	C6/4	option	12	30	27.5	32	33
LSA 42.3L9	J6/4	C6/4	option	12	36	33	38	39.5
LSA 44.3S2	J6/4	C6/4	option	12	42	38	45	46
LSA 44.3S3	J6/4	C6/4	option	12	48	44	51	53
LSA 44.3S4	J6/4	C6/4	option	12	54	49	57	59
LSA 44.3S5	J6/4	C6/4	option	12	60	55	64	66
LSA 44.3M6	J6/4	C6/4	option	12	67	61	71	74
LSA 44.3M8	J6/4	C6/4	option	12	73	66	77	80
LSA 44.3L10	J6/4	C6/4	option	12	80	73	85	88
LSA 44.3L12	J6/4	C6/4	option	12	88	80	93	97
LSA 44.3VL13	J6/4	C6/4	option	12	90	82	95	99
LSA 44.3VL14	J6/4	C6/4	option	12	96	87	102	106
LSA 46.3S4	J6/4	C6/4	option	12	138	126	146	152
LSA 46.3S5	J6/4	C6/4	option	12	144	132	153	158
LSA 46.3M7	J6/4	C6/4	option	12	165	150	175	182
LSA 46.3M8	J6/4	C6/4	option	12	174	158	185	193
LSA 46.3L10	J6/4	C6/4	option	12	195	177	207	215
LSA 46.3L11	J6/4	C6/4	option	12	201	183	216	222

					kVA: 240V 50Hz FF			
励磁系统					持续		备用	备用
型号	SHUNT	AREP	PMG	出线	H:125K	F:105K	H:150K	H:163K
LSA 40VS1	J6/4	C6/4	NA	12	7	6.5	7.5	8
LSA 40VS2	J6/4	C6/4	NA	12	9	8	9.5	10
LSA 40S3	J6/4	C6/4	NA	12	10.5	10	11.5	12
LSA 40S4	J6/4	C6/4	NA	12	12.5	11.5	13.5	14
LSA 40M5	J6/4	C6/4	NA	12	14	13	15	15.5
LSA 40M7	J6/4	C6/4	option	12	15	14	16	16.5
LSA 42.3VS2	J6/4	C6/4	option	12	16	14.5	17	17.5
LSA 42.3VS3	J6/4	C6/4	option	12	19	17.5	20	21,0
LSA 42.3S4	J6/4	C6/4	option	12	22	20	23.5	24
LSA 42.3S5	J6/4	C6/4	option	12	25	23	26.5	27.5
LSA 42.3M7	J6/4	C6/4	option	12	27	24.5	28.5	29.5
LSA 42.3M8	J6/4	C6/4	option	12	30	27.5	32	33
LSA 42.3L9	J6/4	C6/4	option	12	36	33	38	39.5
LSA 44.3S2	J6/4	C6/4	option	12	42	38	45	46
LSA 44.3S3	J6/4	C6/4	option	12	48	44	51	53
LSA 44.3S4	J6/4	C6/4	option	12	54	49	57	59
LSA 44.3S5	J6/4	C6/4	option	12	60	55	64	66
LSA 44.3M6	J6/4	C6/4	option	12	67	61	71	74
LSA 44.3M8	J6/4	C6/4	option	12	73	66	77	80
LSA 44.3L10	J6/4	C6/4	option	12	80	73	85	88
LSA 44.3L12	J6/4	C6/4	option	12	88	80	93	97
LSA 44.3VL13	J6/4	C6/4	option	12	90	82	95	99
LSA 44.3VL14	J6/4	C6/4	option	12	100	91	106	110
LSA 46.3S4	J6/4	C6/4	option	12	138	126	146	152
LSA 46.3S5	J6/4	C6/4	option	12	150	137	159	165
LSA 46.3M7	J6/4	C6/4	option	12	165	150	175	182
LSA 46.3M8	J6/4	C6/4	option	12	180	164	191	200
LSA 46.3L10	J6/4	C6/4	option	12	195	177	207	215
LSA 46.3L11	J6/4	C6/4	option	12	210	191	225	231

LSA 三相改单相 60Hz 220V/230V 功率。

					kVA: 220V 60Hz FF			
励磁系统					持续		备用	备用
型号	SHUNT	AREP	PMG	出线	H:125K	F:105K	H:150K	H:163K
LSA 40VS1	J6/4	C6/4	NA	12	8.2	7.8	8.7	9.2
LSA 40VS2	J6/4	C6/4	NA	12	10.5	9.6	11	11.5
LSA 40S3	J6/4	C6/4	NA	12	12	11	12.8	13.3
LSA 40S4	J6/4	C6/4	NA	12	13,3	12,0	14,2	14,7
LSA 40M5	J6/4	C6/4	NA	12	14,7	13,7	15,6	16,0
LSA 40M7	J6/4	C6/4	NA	12	16,0	14,0	17,0	18,0
LSA 42.3VS1	J6/4	C6/4	option	12	17,3	15,6	18,3	19,0
LSA 42.3VS2	J6/4	C6/4	option	12	17,6	16,0	18,8	19,3
LSA 42.3VS3	J6/4	C6/4	option	12	21,0	19,2	22,4	23,4
LSA 42.3S4	J6/4	C6/4	option	12	22,0	20,0	23,4	24,3
LSA 42.3S5	J6/4	C6/4	option	12	25,2	23,0	26,6	28,0
LSA 42.3M7	J6/4	C6/4	option	12	27,5	25,2	29,3	30,2
LSA 42.3M8	J6/4	C6/4	option	12	31,0	28,4	33,0	34,4
LSA 42.3L9	J6/4	C6/4	option	12	35,7	32,5	38,0	39,4
LSA 44.3S2	J6/4	C6/4	option	12	42	39	45	47
LSA 44.3S3	J6/4	C6/4	option	12	48	43	50	52
LSA 44.3S4	J6/4	C6/4	option	12	54	50	58	60
LSA 44.3S5	J6/4	C6/4	option	12	60	54	63	66
LSA 44.3M6	J6/4	C6/4	option	12	70	63	74	77
LSA 44.3M8	J6/4	C6/4	option	12	74	68	79	82
LSA 44.3L10	J6/4	C6/4	option	12	87	79	93	96
LSA 44.3L12	J6/4	C6/4	option	12	96	88	102	106
LSA 44.3VL13	J6/4	C6/4	option	12	104	93	109	114
LSA 44.3VL14	J6/4	C6/4	option	12	115	104	122	125
LSA 46.3S4	J6/4	C6/4	option	12	139	126	147	153
LSA 46.3S5	J6/4	C6/4	option	12	151	137	160	167
LSA 46.3M7	J6/4	C6/4	option	12	167	151	176	183
LSA 46.3M8	J6/4	C6/4	option	12	183	165	192	200
LSA 46.3L10	J6/4	C6/4	option	12	197	179	208	216
LSA 46.3L11	J6/4	C6/4	option	12	212	192	229	233

					kVA: 230V 60Hz FF			
励磁系统					持续		备用	
型号	SHUNT	AREP	PMG	出线	H:125K	F:105K	H:150K	H:163K
LSA 40VS1	J6/4	C6/4	NA	12	8.6	8.1	9.1	9.6
LSA 40VS2	J6/4	C6/4	NA	12	11	10	11.5	12,0
LSA 40S3	J6/4	C6/4	NA	12	12,5	11,5	13,4	14,0
LSA 40S4	J6/4	C6/4	NA	12	14,0	12,5	14,8	15,3
LSA 40M5	J6/4	C6/4	NA	12	15,3	14,4	16,3	16,8
LSA 40M7	J6/4	C6/4	NA	12	16,8	15,0	17,7	18,7
LSA 42.3VS1	J6/4	C6/4	option	12	18,0	16,3	19,2	20,0
LSA 42.3VS2	J6/4	C6/4	option	12	18,4	16,8	19,6	20,2
LSA 42.3VS3	J6/4	C6/4	option	12	22,0	20,0	23,5	24,4
LSA 42.3S4	J6/4	C6/4	option	12	23,0	21,0	24,4	25,4
LSA 42.3S5	J6/4	C6/4	option	12	26,3	24,0	27,8	29,0
LSA 42.3M7	J6/4	C6/4	option	12	28,7	26,3	30,6	31,6
LSA 42.3M8	J6/4	C6/4	option	12	32,6	29,7	34,5	35,9
LSA 42.3L9	J6/4	C6/4	option	12	37,4	34,0	39,8	41,2
LSA 44.3S2	J6/4	C6/4	option	12	44	40	47	49
LSA 44.3S3	J6/4	C6/4	option	12	50	45	53	55
LSA 44.3S4	J6/4	C6/4	option	12	57	52	60	62
LSA 44.3S5	J6/4	C6/4	option	12	62	57	66	67
LSA 44.3M6	J6/4	C6/4	option	12	73	66	78	81
LSA 44.3M8	J6/4	C6/4	option	12	78	71	82	85
LSA 44.3L10	J6/4	C6/4	option	12	91	82	97	101
LSA 44.3L12	J6/4	C6/4	option	12	101	92	106	111
LSA 44.3VL13	J6/4	C6/4	option	12	108	98	114	119
LSA 44.3VL14	J6/4	C6/4	option	12	120	109	127	130
LSA 46.3S4	J6/4	C6/4	option	12	146	132	154	160
LSA 46.3S5	J6/4	C6/4	option	12	158	144	168	174
LSA 46.3M7	J6/4	C6/4	option	12	174	158	184	192
LSA 46.3M8	J6/4	C6/4	option	12	192	172	201	209
LSA 46.3L10	J6/4	C6/4	option	12	206	187	217	226
LSA 46.3L11	J6/4	C6/4	option	12	221	201	240	243

LSA 40 专用单相 60Hz/220V 时功率有折扣，功率表如下：

	<b>Available powers for LSA40 at 220V/60Hz andPF1</b>			
<b>machines</b>	<b>class H, S1, 40°C</b>	<b>class F, S1, 40°C</b>	<b>class H, S2, 40°C</b>	<b>class H,S2, 27°C</b>
LSA40 VS1	11 kVA	10 kVA	11,7 kVA	12,1 kVA
LSA40 VS2	13 kVA	11,8 kVA	13,8 kVA	14,3 kVA
LSA40 S3	13,5 kVA	12,3 kVA	14,3 kVA	14,9 kVA
LSA40 S4	14,5 kVA	13,2kVA	15,4 kVA	16 kVA
LSA40 M5	16,5 kVA	15 kVA	17,5 kVA	18,2 kVA

TAL 三相改单相 50Hz 220V/240V 功率。

					kVA: 220V 50Hz FF			
励磁系统					持续		备用	备用
型号	SHUNT	AREP	PMG	出线	H:125K	F:105K	H:150K	H:163K
TAL-A40-C	J6/4	C6/4	NA	12	7	6	7.5	8
TAL-A40-D	J6/4	C6/4	NA	12	9	8	9.5	10.3
TAL-A40-E	J6/4	C6/4	NA	12	10.5	9.5	11	12
TAL-A40-F	J6/4	C6/4	NA	12	12	11	12.5	13.4
TAL-A40-G	J6/4	C6/4	NA	12	15	13.5	16	16.6
TAL-A42-C	J6/4	C6/4	option	12	17,2	15,3	18,2	18,9
TAL-A42-E	J6/4	C6/4	option	12	22	19,6	23	24,2
TAL-A42-F	J6/4	C6/4	option	12	24	21,5	25	26,4
TAL-A42-G	J6/4	C6/4	option	12	26	23	27	28,7
TAL-A42-H	J6/4	C6/4	option	12	34	31	36	38
TAL-A44-C	J6/4	C6/4	option	12	40	36	42	44
TAL-A44-D	J6/4	C6/4	option	12	48	43	50.5	53
TAL-A44-E	J6/4	C6/4	option	12	57	51	60	63
TAL-A44-H	J6/4	C6/4	option	12	67	60	70.5	74
TAL-A44-J	J6/4	C6/4	option	12	70	63	73,5	76,5
TAL-A44-K	J6/4	C6/4	option	12	76	69	80	84
TAL-A44-L	J6/4	C6/4	option	12	90	82	95	99
TAL-A44-M	J6/4	C6/4	option	12	96	87	102	106
TAL-A46-C	J6/4	C6/4	option	12	138	126	146	152
TAL-A46-D	J6/4	C6/4	option	12	144	132	153	158
TAL-A46-E	J6/4	C6/4	option	12	165	150	175	182
TAL-A46-F	J6/4	C6/4	option	12	174	158	185	191
TAL-A46-G	J6/4	C6/4	option	12	195	177	207	215
TAL-A46-H	J6/4	C6/4	option	12	201	183	214	222

					kVA: 240V 50Hz FF			
励磁系统					持续		备用	备用
型号	SHUNT	AREP	PMG	出线	H:125K	F:105K	H:150K	H:163K
TAL-A40-C	J6/4	C6/4	NA	12	7	6	7.5	8
TAL-A40-D	J6/4	C6/4	NA	12	9	8	9.5	10.3
TAL-A40-E	J6/4	C6/4	NA	12	10.5	9.5	11	12
TAL-A40-F	J6/4	C6/4	NA	12	12	11	12.5	13.4
TAL-A40-G	J6/4	C6/4	NA	12	15	13.5	16	16.6
TAL-A42-C	J6/4	C6/4	option	12	18	16	19	19.8
TAL-A42-E	J6/4	C6/4	option	12	22.8	20.5	24	25.6
TAL-A42-F	J6/4	C6/4	option	12	25	22.5	26	28
TAL-A42-G	J6/4	C6/4	option	12	27	24	28	30
TAL-A42-H	J6/4	C6/4	option	12	36	32.5	38	40
TAL-A44-C	J6/4	C6/4	option	12	42	38	44	46
TAL-A44-D	J6/4	C6/4	option	12	46	41	48	51
TAL-A44-E	J6/4	C6/4	option	12	57	51	60	63
TAL-A44-H	J6/4	C6/4	option	12	62	56	65.5	66
TAL-A44-J	J6/4	C6/4	option	12	70	63	73,5	76,5
TAL-A44-K	J6/4	C6/4	option	12	76	69	80	84
TAL-A44-L	J6/4	C6/4	option	12	90	82	95	99
TAL-A44-M	J6/4	C6/4	option	12	100	91	106	110
TAL-A46-C	J6/4	C6/4	option	12	138	126	146	152
TAL-A46-D	J6/4	C6/4	option	12	150	137	159	165
TAL-A46-E	J6/4	C6/4	option	12	165	150	175	182
TAL-A46-F	J6/4	C6/4	option	12	180	164	191	198
TAL-A46-G	J6/4	C6/4	option	12	195	177	207	215
TAL-A46-H	J6/4	C6/4	option	12	210	191	223	231

TAL 三相改单相 60Hz 220V/230V 功率

					kVA: 220V 60Hz FF			
励磁系统					持续		备用	备用
型号	SHUNT	AREP	PMG	出线	H:125K	F:105K	H:150K	H:163K
TAL-A40-C	J6/4	C6/4	NA	12	8,2	7,3	8,7	9
TAL-A40-D	J6/4	C6/4	NA	12	10,6	9,5	11	12
TAL-A40-E	J6/4	C6/4	NA	12	12	11	12,8	13
TAL-A40-F	J6/4	C6/4	NA	12	12,8	11,5	13,4	13,7
TAL-A40-G	J6/4	C6/4	NA	12	15,6	14,1	16,5	17,4
TAL-A42-C	J6/4	C6/4	option	12	19,6	17,8	20,7	21,5
TAL-A42-E	J6/4	C6/4	option	12	23	21	24	25,3
TAL-A42-F	J6/4	C6/4	option	12	25,6	23	26,6	28
TAL-A42-G	J6/4	C6/4	option	12	28	25	29,3	31
TAL-A42-H	J6/4	C6/4	option	12	36	32	37,6	39,4
TAL-A44-C	J6/4	C6/4	option	12	47,6	43	50	52
TAL-A44-D	J6/4	C6/4	option	12	60	53,6	62,3	66
TAL-A44-E	J6/4	C6/4	option	12	70	62,6	73	76
TAL-A44-H	J6/4	C6/4	option	12	74	67	78	81,5
TAL-A44-J	J6/4	C6/4	option	12	87	78	92	96
TAL-A44-K	J6/4	C6/4	option	12	96	86,6	101	105
TAL-A44-L	J6/4	C6/4	option	12	104	93	109	114
TAL-A44-M	J6/4	C6/4	option	12	115	104	122	125
TAL-A46-C	J6/4	C6/4	option	12	139	126	148	153
TAL-A46-D	J6/4	C6/4	option	12	151	137	160	167
TAL-A46-E	J6/4	C6/4	option	12	167	152	177	183
TAL-A46-F	J6/4	C6/4	option	12	183	167	194	202
TAL-A46-G	J6/4	C6/4	option	12	197	180	209	217
TAL-A46-H	J6/4	C6/4	option	12	212	192	224	233

					kVA: 230V 60Hz FF			
励磁系统					持续		备用	备用
型号	SHUNT	AREP	PMG	出线	H:125K	F:105K	H:150K	H:163K
TAL-A40-C	J6/4	C6/4	NA	12	8,6	7,7	9	9,6
TAL-A40-D	J6/4	C6/4	NA	12	11	10	11,5	12,5
TAL-A40-E	J6/4	C6/4	NA	12	12,5	11,5	13,4	13,4
TAL-A40-F	J6/4	C6/4	NA	12	13,4	12	14	14,4
TAL-A40-G	J6/4	C6/4	NA	12	16	15	17	18
TAL-A42-C	J6/4	C6/4	option	12	20,5	18,6	21,6	22,5
TAL-A42-E	J6/4	C6/4	option	12	24	22	25	26,4
TAL-A42-F	J6/4	C6/4	option	12	26,8	24	28	29
TAL-A42-G	J6/4	C6/4	option	12	29	26,3	30,7	32
TAL-A42-H	J6/4	C6/4	option	12	37,4	33,5	39,3	41
TAL-A44-C	J6/4	C6/4	option	12	50	45	52	55
TAL-A44-D	J6/4	C6/4	option	12	62	56	65	68
TAL-A44-E	J6/4	C6/4	option	12	72,5	65,4	76,5	79
TAL-A44-H	J6/4	C6/4	option	12	77	70	81	85
TAL-A44-J	J6/4	C6/4	option	12	91	82	95,5	100
TAL-A44-K	J6/4	C6/4	option	12	100	90	105	110
TAL-A44-L	J6/4	C6/4	option	12	108	98	114	119
TAL-A44-M	J6/4	C6/4	option	12	120	109	127	130
TAL-A46-C	J6/4	C6/4	option	12	146	132	154	160
TAL-A46-D	J6/4	C6/4	option	12	158	144	168	174
TAL-A46-E	J6/4	C6/4	option	12	174	159	185	192
TAL-A46-F	J6/4	C6/4	option	12	192	174	203	211
TAL-A46-G	J6/4	C6/4	option	12	206	188	218	227
TAL-A46-H	J6/4	C6/4	option	12	221	201	235	243

TAL-A40-S 专用单相 60Hz/220V 时功率有折扣，功率表如下：

TAL-A40-S at 220V/60Hz PF=1				
machines	class H,S1, 40°C	class F,S1, 40°C	class H,S2, 40°C	class H,S2, 27°C
TAL-A40-C-S	11kVA	10kVA	11,7kVA	12,1kVA
TAL-A40-C1-S	13kVA	11,8kVA	13,8kVA	14,3kVA
TAL-A40-D-S	13,5kVA	12,3kVA	14,3kVA	14,9kVA
TAL-A40-E-S	14,5kVA	13,2kVA	15,4kVA	16kVA
TAL-A40-F-S	16,5kVA	15kVA	17,5kVA	18,2kVA